
Motion detector

IS 1 black EAN 4007841 600419 Article number 600419







Function description

Targeted detection and attractive price. Infrared motion detector IS 1, for indoors and out, ideal for targeted coverage of small areas, 120° angle of coverage, reach up to 10 m, selectable time and twilight threshold, sensor turns through 30° and tilts through 180° for exact adjustment of the detection zone.

Technical specifications

Dimensions (L x W x H)	120 x 80 x 50 mm	LED lamps < 2 W	16 W
Manufacturer's Warranty	3 years	LED lamps > 2 W < 8 W	64 W
Settings via	Potentiometers	LED lamps > 8 W	64 W
With remote control	No	Capacitive load in µF	88 µF
Version	black	Technology, sensors	passive infrared, Light sensor
PU1, EAN	4007841600419	Mounting height	1,80 – 3,00 m
Туре	Motion detectors	Mounting height max.	3,00 m
Application, place	Indoors, Outdoors	Optimum mounting height	2 m
Application, room	outdoors, front door, all round the	Detection angle	120 °
	building, terrace / balcony, courtyard & driveway	Angle of aperture	40 °
Colour	black	Sneak-by guard	No
Colour, RAL	9005	Capability of masking out individual segments	Yes
Includes corner wall mount	No	Electronic scalability	No
Installation site	wall, ceiling	Mechanical scalability	No
Installation	Surface wiring, Wall, Ceiling	Reach. radial	$r = 3 m (9 m^2)$
IP-rating	IP54	Reach, tangential	$r = 10 \text{ m} (105 \text{ m}^2)$
Protection class	II		1 – 10 m (100 m)

09.2023 Page 1 from 3

IS 1

black EAN 4007841 600419 Article number 600419



Technical specifications


-20 - 50 °C			
Plastic			
230 – 240 V / 50 Hz			
500 W			
4 pcs.			
Fluorescent lamps, electronic ballast430 W			
500 VA			

260 switching zones	
2 – 2000 lx	
8 s – 35 Min.	
No	
No	
No	
No	
Yes	
Master/master	
Cable	

IS 1 black EAN 4007841 600419 Article number 600419




Detection Zone




Possible mounting height: 1,80 m- 3,00 m Orange: radial Black: tangential


Light without neutral conductor




Connection using two-circuit switch for manual and automatic operation



Dimension Drawing



Light with neutral conductor



Circuit diagram Connection via a changeover switch for continuous and automatic operation

