

F&F Filipowski sp. j. Konstantynowska 79/81 95-200 Pabianic phone/fax: (+48 42) 215 23 83 / 227 09 71 POLAND http://www.fif.com.pl e-mail: fif@fif.com.pl

ELECTRONIC BI-STABLE **PULSE RELAY** 

**BIS-411** 230V


WARRANTY. The F&F products are covered by a warranty of the 24 months from the date of purchase. Effective only with proof of purchase. Contact your dealeror directly with us. More information how to make a compliant can be found on the website: <a href="https://www.fif.com.pl/reklamacie">www.fif.com.pl/reklamacie</a>





### **PURPOSE**

Electronic bi-stable pulse relays BIS-411 230V enables the user to actuate lighting or other devices from various locations by means of control buttons in parallel connection.





- 1 -

## TECHNICAL DATA

power supply contact / current load AC-1 separated 1 C/O / 16A control pulse 110÷265V AC < 20mA max current control buttons activation delay signalling of supply signalling of activation power consumption standby working temperature connection 2,5mm<sup>2</sup> screw terminals tightening torque dimensions 1 module (18mm) fixing on the TH-35 rail ingress protection

# WIRING DIAGRAM





230V AC

Σ5mA

0.1÷0.2sec

green LED

0,15W 0.6W -25÷50°C

0.4 Nm

IP20

SUPPLY

1-3 power relay: 100-265V AC CONTROL INPUTS

control inputs

CONTACT

power input contact COM

10 output: NC contact (passive)

12 output: NO contact (active)

### **FUNCTIONING**

The receiver is actuated by means of a current pulse triggered by pushing any bell push connected to the relay. The receiver is deactivated by another pulse or after a preset time. The relay does not "memorize" the position of the relay contact, i.e. in case of supply voltage decay and the subsequent return of supply voltage, the relay contact will be set in the off position. Such a solution prevents the automatic actuation of the receivers controlled that might occur without proper supervision after a long-lasting decay of supply voltage.

## ASSEMBLY

- 1. Turn OFF the power.
- 2. Put on the relay on the rail in the switchgear box.
- 3. Connect the power cable to contacts 1-3 with accordance choosen control option the relay (control impulse Lor N).
- 4.The timers switching which are connect in parallel connect to contact 6 and to cable which is connect to contact 3.
- 5. The activated receiver connect in series to contacts 11-12.
- 6. By screwdriver set to switching OFF delay.


### ATTENTION!

The BIS-411 230V is compatible with bell pushes equipped with fluorescent lamps (ΣI<5mA).



- 2 -

### Example of relay connection with N control pulse



## Table of power



The above data are indicative and will heavily depend on the design of a specific receiver (that is especially important for LED bulbs, energy-saving lamps, electronic transformers and pulse power supply units), switching frequency and operating conditions.

For more information visit www.fif.com.pl

D150203/150520 - 4 -