






## **KALU TRACK**

spot for 240V 3-phase track, QPAR111, white, max. 75 W, incl. 3-phase adapter

Adjustable spot KALU TRACK with suitable adapter for the 240V 3-phase track system. Conceived as an extension to the popular KALU series, this track spot takes on the shape of the product family. By the incorporated GU10 lamp holder, the spot is suitable to take LED and halogen ES111 lamps. To meet all lighting requirements, we alternatively offer versions with G53 socket and such with incorporated Philips LED modules for the 1- and 3-phase systems.



## **TECHNICAL DATA**

Item no.:	152611
Socket	GU10
Lamp	QPAR111
Number of sockets	1
Lamps included	No
Primary nominal voltage	220-240V ~50/60Hz mA/V
Tiltrange	90 °
Horizontal rotation range	350 °
Length	18 cm
Diameter	12 cm
Net weight	0.313 kg
Gross weight	0.426 kg
IP Code	IP 20
Safety class	II
Assembly	Surface
Assembly details	Ceiling, Track Ceiling, Track Wall, Wall
Wattage	75 W
Color	white
BIG WHITE Page	454
	1



## Recommended lamp

1005274	QPAR111 GU10 , trans- parent LED light, 8W 2700K CRI90 38°
1005276	QPAR111 GU10 , silver LED light, 12.5W 2700K CRI90 30°
1005282	QPAR111 GU10 , silver LED light, 12.5W 4000K CRI90 30°
1005298	